

KiraQG2 http GET commands

Replace the three digit number with the required function. For example;

<http://192.xxx.xxx.xxx/code.htm?button012> will send the command “power”

<http://192.xxx.xxx.xxx/code.htm?button062> will send the command “play”

012 = Power
128 = Sky
204 = TV Guide
125 = Box office
126 = Services
245 = Interactive
203 = Info
088 = Up
089 = Down
090 = Left
091 = Right
092 = Select
032 = Ch Up
033 = Ch Dn
060 = Text
131 = Backup
129 = Help
061 = Rewind
036 = Pause
062 = Play
040 = FastForward
064 = Record
063 = Stop
109 = Red
110 = Green
111 = Yellow
112 = Blue
001 = One
002 = Two
003 = Three
004 = Four
005 = Five
006 = Six
007 = Seven
008 = Eight
009 = Nine
000 = Zero